

# ABB i-bus® KNX

## Lighting Control

■ = Function is supported

– = Function is not supported

1) = Selected LED retrofit lamps are tested and approved. Restrictions have to be observed. Details see Busch-Dimmer® Tool (www.busch-jaeger.com)

2) = One channel uses 500 W

3) = See maximum load per channel

	Universal Dim Actuators		
	UD/S x.210.2.1	UD/S x.315.2.1	6197/15-101-500
<b>General</b>			
Supply voltage	110 – 230 V AC ± 10 %, 50/60 Hz	110 – 230 V AC ± 10 %, 50/60 Hz	230 V AC ± 10 %, 50/60 Hz
Type of installation	DIN-Rail	DIN-Rail	DIN-Rail
Module width (space unit)	6/8	4/8/12	8/12
Number of outputs	4/6	2/4/6	1, 4, 6
Maximum load per channel	4 x 210 W (1 x 600 W)/ 6 x 210 W (1 x 800 W)	2 x 315 W (1 x 500 W) 4 x 315 W (2 x 500 W) 6 x 315 W (2 x 700 W or 3 x 500 W)	210, 315, 600, 1260, 2400 VA
Incoming supply	4/6 phase inputs	2/4/6 phase inputs	3 phase inputs
<b>Load types</b>			
230 V incandescent lamps	■	■	■
230 V halogen lamps	■	■	■
Low-voltage halogen lamps with conventional transformers or electronic transformers	■	■	■
LED strips or 12/24 V lamps	–	–	–
LED Retrofit 230 V	■	–	■ <sup>1)</sup>
Grouping of channels for load increase	■	■ <sup>3)</sup>	■
<b>Switching</b>			
Brightness value when turned on	■	■	■
Dimming speed for switching on and off	■	■	■
<b>Dimming</b>			
Min. and max. dimming values	■	■	■
Switching on/off via rel. dimming	■	■	■
<b>Further functions</b>			
Forced operation	■	■	–
Dimming curve adjustment	■	■	■
Reaction on bus voltage failure	■	■	■
Behavior on bus voltage recovery	■	■	■
Status feedback	■	■	■
Blocking channel	■	■	■
Scenes	■	■	■
Phase angle control: automatic, leading or trailing edge	■	■	■
Additional logic functions	■	■	■
Staircase lighting	■	■	■

# ABB i-bus® KNX

## Lighting Control

- = Function is supported
- = Function is not supported

	LED Dimmer with constant curve	
	6155/30-500 1-4-fold	6155/40-500 1-4-fold with power supply
<b>General</b>		
Supply voltage	12...24 V DC	230 V AC ± 10%, 50/60 Hz
Type of installation	Wall (surface)	Wall (surface)
Module width (space unit)	-	-
Number of outputs	4	4
Maximum load per channel	1 x 10 A/ 4 x 2.5 A	1 x 4 A/ 4 x 1 A
Incoming supply	1 phase input	1 phase input
<b>Load types</b>		
230 V incandescent lamps	-	-
230 V halogen lamps	-	-
Low-voltage halogen lamps with conventional transformers or electronic transformers	-	-
LED strips or 12/24 V lamps	■	■
LED Retrofit 230 V	-	-
Grouping of channels for load increase	■	■
<b>Switching</b>		
Brightness value when turned on	■	■
Dimming speed for switching on and off	■	■
<b>Dimming</b>		
Min. and max. dimming values	■	■
Switching on/off via rel. dimming	■	■
<b>Further functions</b>		
Forced operation	-	-
Dimming curve adjustment	-	-
Reaction on bus voltage failure	-	-
Behavior on bus voltage recovery	■	■
Status feedback	■	■
Blocking channel	■	■
Scenes	■	■
Phase angle control: automatic, leading or trailing edge	-	-
Additional logic functions	-	-
Staircase lighting	-	-

# ABB i-bus® KNX

## Lighting Control

- = Function is supported
- = Function is not supported
- 1) = The maximum peak inrush current may not be exceeded

	Switch/Dim Actuators			Constant Light Control	
	SD/S 2.16.1	SD/S 4.16.1	SD/S 8.16.1	LR/S 2.16.1	LR/S 4.16.1
<b>General</b>					
Supply voltage	KNX	KNX	KNX	KNX	KNX
Type of installation	DIN-Rail	DIN-Rail	DIN-Rail	DIN-Rail	DIN-Rail
Module width (space unit)	4	6	8	4	6
Number of outputs 1-10 V (passive)	2	4	8	2	4
Manual operation	■	■	■	■	■
Maximum current per control output	100 mA	100 mA	100 mA	100 mA	100 mA
Maximum cable length at maximum load (100 mA)	70 m (cable cross-section 0.8 mm <sup>2</sup> )	70 m (cable cross-section 0.8 mm <sup>2</sup> )	70 m (cable cross-section 0.8 mm <sup>2</sup> )	70 m (cable cross-section 0.8 mm <sup>2</sup> )	70 m (cable cross-section 0.8 mm <sup>2</sup> )
	100 m (cable cross-section 1.5 mm <sup>2</sup> )	100 m (cable cross-section 1.5 mm <sup>2</sup> )	100 m (cable cross-section 1.5 mm <sup>2</sup> )	100 m (cable cross-section 1.5 mm <sup>2</sup> )	100 m (cable cross-section 1.5 mm <sup>2</sup> )
Light sensor (LF/U 2.1)	-	-	-	2	4
Maximum cable length per sensor (P-YCYM or J-Y(ST)Y cable (SELV), diameter 0.8 mm)	-	-	-	100 m	100 m
Power loss per device at max. load	2.6 W	5.2 W	10.4 W	2.6 W	5.2 W
<b>Switching capacity</b>					
Rated current I <sub>n</sub>	16 A AC1	16 A AC1	16 A AC1	16 A AC1	16 A AC1
Rated voltage U <sub>n</sub>	250/440 V AC	250/440 V AC	250/440 V AC	250/440 V AC	250/440 V AC
AC1 operation (cos φ = 0.8) DIN EN 60 947-4-1	16 A	16 A	16 A	16 A	16 A
AC3 operation (cos φ = 0.45) DIN EN 60 947-4-1	8 A/ 230 V	8 A/ 230 V	8 A/ 230 V	8 A/ 230 V	8 A/ 230 V
Fluorescent lighting load AX DIN EN 60 669-1	10 A (140 μF) <sup>1)</sup>	10 A (140 μF) <sup>1)</sup>	10 A (140 μF) <sup>1)</sup>	10 A (140 μF) <sup>1)</sup>	10 A (140 μF) <sup>1)</sup>
Minimum switching capacity	100 mA/12 V	100 mA/12 V	100 mA/12 V	100 mA/12 V	100 mA/12 V
DC current switching capacity (resistive load)	10 A/24 V DC	10 A/24 V DC	10 A/24 V DC	10 A/24 V DC	10 A/24 V DC
Mechanical service life	> 3 x 10 <sup>6</sup>	> 3 x 10 <sup>6</sup>	> 3 x 10 <sup>6</sup>	> 3 x 10 <sup>6</sup>	> 3 x 10 <sup>6</sup>
<b>Electronic endurance to DIN IEC 60 947-4-1</b>					
Rated current AC1 (240 V/cos φ = 0.8)	100,000	100,000	100,000	100,000	100,000
Rated current AC3 (240 V/cos φ = 0.45)	30,000	30,000	30,000	30,000	30,000
Rated current AC5a (240 V/cos φ = 0.45)	30,000	30,000	30,000	30,000	30,000
Incandescent lamp load at 230 V AC	2,300 W	2,300 W	2,300 W	2,300 W	2,300 W
<b>Fluorescent lamps T5/T8</b>					
Uncorrected	2,300 W	2,300 W	2,300 W	2,300 W	2,300 W
Parallel compensated	1,500 W	1,500 W	1,500 W	1,500 W	1,500 W
DUO circuit	1,500 W	1,500 W	1,500 W	1,500 W	1,500 W
<b>Low-voltage halogen lamps</b>					
Inductive transformer	1,200 W	1,200 W	1,200 W	1,200 W	1,200 W
Electronic transformer	1,500 W	1,500 W	1,500 W	1,500 W	1,500 W
Halogen lamp 230 V	2,500 W	2,500 W	2,500 W	2,500 W	2,500 W
<b>Dulux lamps</b>					
Uncorrected	1,100 W	1,100 W	1,100 W	1,100 W	1,100 W
Parallel compensated	1,100 W	1,100 W	1,100 W	1,100 W	1,100 W
<b>Mercury-vapour lamps</b>					
Inductive transformer	2,000 W	2,000 W	2,000 W	2,000 W	2,000 W
Electronic transformer	2,000 W	2,000 W	2,000 W	2,000 W	2,000 W

# ABB i-bus® KNX

## Lighting Control

- = Function is supported
- = Function is not supported
- 1) = For multiple element lamps or other types, the number of electronic ballasts must be determined using the peak inrush current of the electronic ballasts

	Switch/Dim Actuators			Constant Light Control	
	SD/S 2.16.1	SD/S 4.16.1	SD/S 8.16.1	LR/S 2.16.1	LR/S 4.16.1
<b>Sodium-vapour lamps</b>					
Inductive transformer	2,000 W	2,000 W	2,000 W	2,000 W	2,000 W
Electronic transformer	2,000 W	2,000 W	2,000 W	2,000 W	2,000 W
Max. peak inrush-current I <sub>p</sub> (150 μs)	400 A	400 A	400 A	400 A	400 A
Max. peak inrush-current I <sub>p</sub> (250 μs)	320 A	320 A	320 A	320 A	320 A
Max. peak inrush-current I <sub>p</sub> (600 μs)	200 A	200 A	200 A	200 A	200 A
<b>Number of ballasts (T5/T8, single element) e.g.<sup>1)</sup></b>					
18 W (ABB EVG 1 x 18 SF)	23	23	23	23	23
24 W (ABB EVG 1 x 24 CY)	23	23	23	23	23
36 W (ABB EVG 1 x 36 CF)	14	14	14	14	14
58 W (ABB EVG 1 x 58 CF)	11	11	11	11	11
80 W (Helvar EL 1 x 80 SC)	10	10	10	10	10

	Switch/Dim Actuators			Constant Light Control	
	SD/S 2.16.1	SD/S 4.16.1	SD/S 8.16.1	LR/S 2.16.1	LR/S 4.16.1
<b>Functions</b>					
Brightness control	-	-	-	■	■
Brightness value	■	■	■	■	■
Dimming speed for transition brightness values	■	■	■	■	■
Min. and max. value limits	■	■	■	■	■
Set switching on and off via value	■	■	■	■	■
Presets	■	■	■	■	■
Scenes	■	■	■	■	■
<b>Switch</b>					
Brightness value when turned on	■	■	■	■	■
Dimming speed for switching on and off	■	■	■	■	■
<b>Dimming</b>					
Dimming speed can be changed via KNX	■	■	■	■	■
Min. and max. dimming values	■	■	■	■	■
Switching on/off via rel. dimming	■	■	■	■	■
<b>Forced operation</b>					
2-bit coded forced operation	■	■	■	■	■
Behaviour after voltage recovery	■	■	■	■	■
Block Activate output via 1-bit object	■	■	■	■	■
<b>Special</b>					
4-point characteristic adjustment	■	■	■	■	■
Preference with bus voltage failure	■	■	■	■	■
Status feedback	■	■	■	■	■
<b>Additional</b>					
Slave mode e.g. for integration in the constant lighting control	■	■	■	■	■
Staircase lighting	■	■	■	■	■
Prewarning via dimming and/or KNX object	■	■	■	■	■
<b>Commissioning and diagnostic functions</b>					
Control and diagnosis via ABB i-bus® Tool	-	-	-	■	■