

## Berker TS Sensor Glass sensor 2gang glass, aluminium



**Order no. 1682 07** ✱  
Packing unit 1

Operating voltage 8 - 30 V=  
Current consumption (operation) approx. 26 mA  
Switching voltage max. 30 V=  
Switching current max. 10 mA  
LED input voltage max. 5 V~/=  
LED input current max. 1 mA  
Surface adjustment 20 mm

### for order-no.

Best.-Nr. 7590 00 31

Best.-Nr. 7590 00 32

**flush wall-mounting possible with wall box 2gang for glass sensor order no.**

Best.-Nr. 1870

- separate auxiliary power supply needed
- operation by gently touching the sensor surfaces on the white LED
- the blue LED can be set for Continuously ON or External activation
- the white LED can be set for Sensor operation or External activation
- with adapter ring for disassembly protection, shadow jointing and special installation conditions
- for vertical mounting
- with disassembly suction tool
- --- KNX/EIB ---
- with one blue ON LED and 4 white status LEDs
- for adapting using KNX/EIB adapter 2 x 8gang or wiring with universal adapter
- for parameterisable functions see universal interfaces
- operation with non-choked output of KNX/EIB voltage supply possible (pay attention to current consum
- --- Radio bus ---
- with one blue ON LED and 4 white status LEDs, e.g. as orientation or control LED
- for wiring with universal adapters
- for settable functions see the radio push-button interface
- --- relay ---
- with one blue ON LED and 4 white status LEDs, e.g. as orientation or control LED
- for wiring with universal adapters

Many options for printing see [www.berker.com](http://www.berker.com)

For production-related reasons, with polar white there are colour deviations from the existing glass ranges.