

Product data sheet

KNX RF radio hand-held transmitter 2-gang



Reference number

HS 2 RF

KNX RF radio hand-held transmitter

2-gang

Project design and commissioning with ETS5 or a more recent version.

Intended use

- Radio operation of loads, e.g. light on/off, dimming, Venetian blinds up/down, brightness values, calling up and saving light scenes
- Operation in cabled KNX systems via radio converter (ref.-no.: MK 100 RF)

Product characteristics

- Push-button functions for switching, dimming, blinds control, valuator, light scenes, etc.
- Button pairs for push-button function or rocker function
- Two-colour LED to display actuation, sending status and actuator feedback
- Battery-powered device

Technical data

Rated voltage:	DC 3 V
Battery type:	1 x lithium CR 2450N (included)
Ambient temperature:	-5 ... +45 °C
Relative humidity:	max. 80 % (no condensation)
Radio frequency:	868.0 ... 868.6 MHz
Transmitting power:	max. 20 mW
Transmission range in free field:	typical 100 m

Colour:

anthracite