


ITR630-003 - KNX DND/MUR PANEL



Device	ITR630-003
Power Supply	EIB Power Supply 12V DC for LEDs
Power Consumption	KNX Bus : 5mA 12 - 36V DC : 0.5W
LED Indicators	1 x DND, 1xMUR, 1xOccupied (optional), 1xProgramming
Push Buttons	1 x Programming Button, 1xBell Button
Inputs	Dry Contact Inputs
Maximum Air Humidity	<90RH
Temperature Range	Operation (-5°C...55°C) Storage (-10°C...70°C)
Flammability	Non-flammable product
Dimensions	55x88,1x21,6 mm (WxHxD)
Certification	KNX
Configuration	Configuration with ETS




DESCRIPTION

The ITR630-003 - KNX DND/MUR panel is a simple way for guests to communicate with staff from their room. If the customer do not want to be disturbed, need the room to be cleaned or available for room service it is as simple as touching related buttons. The product includes a doorbell button to announce visitors in a kindly way. Besides, optionally the doorbell can be disabled whether the “Do Not Disturb” is active.

The KNX DND/MUR panel needs an extra 12-36 V DC power supply for LEDs. KNX bus enables information exchanges with KNX devices and the integration with a building management system.

Moreover, the KNX DND/MUR panel can be customized with the room number, icons (Do Not Disturb / Make Up Room / Occupied (optionally), logo. Also, the logo of the hotel can be made on the doorbell button. So, hotels can simply integrate our technology into their own design.


DIMENSIONS



SAFETY INSTRUCTIONS

- Special Programming - This device is designed for professional KNX installation. It can only be programmed by ETS software.
- Cable Connections - Do not get wrong connection for black and red KNX Bus wires. Also, for DC supply be aware of the positive and negative pole connections.
- Voltage - The bus voltage must be between 21-30V DC. DC power supply must be 12-36V DC.
- Mounting Location - A suitable surface outside the respective hotel room.
- Screw down torque is less than 0.8Nm.
- Avoid contact with liquids and corrosive gases.

CONNECTION DIAGRAM



1. 12-36V DC Input
2. Relay for DoorBell